



Art.	Serbatoio Litri	Pompa Mod.	Esecuzione motore Volt	Apparecchiatura elettrica art.	D	F	H	Peso Kg	Accessori Filtro art.
<b>DO 20 VTL 5</b>	20	VTL 5	3 ~ 230/400-50Hz	DO 06 92	320	345	270	38.5	FB 20 / FC 20
<b>DO 20 VTL 5 M</b>	20	VTL 5 M	1 ~ 230/50Hz	DO 06 90	320	345	270	39.0	FB 20 / FC 20
<b>DO 20 VTL 6 CC</b>	20	VTL 6 CC	= 24-CC	DO 06 93	400	295	270	34.3	FB 20 / FC 20
<b>DO 20 VTL 10</b>	20	VTL 10	3 ~ 230/400-50Hz	DO 06 92	352	345	270	44.5	FB 20 / FC 20
<b>DO 20 VTL 10 M</b>	20	VTL 10 M	1 ~ 230-50Hz	DO 06 90	352	345	270	45.0	FB 20 / FC 20
<b>DO 20 VTL 10/F</b>	20	VTL 10/F	3 ~ 230/400-50Hz	DO 06 92	390	360	270	49.0	FB 20 / FC 20
<b>DO 20 VTL 10/F M</b>	20	VTL 10/F M	1 ~ 230-50Hz	DO 06 90	390	360	270	49.5	FB 20 / FC 20
<b>DO 20 VTL 15/F</b>	20	VTL 15/F	3 ~ 230/400-50Hz	DO 06 92	410	360	270	51.0	FB 20 / FC 20
<b>DO 20 VTL 15/F M</b>	20	VTL 15/F M	3 ~ 230/400-50Hz	DO 06 90	410	360	270	51.5	FB 20 / FC 20
<b>DO 20 VTL 20/F</b>	20	VTL 20/F	3 ~ 230/400-50Hz	DO 06 92	430	360	270	54.0	FB 20 / FC 20
<b>DO 20 VTL 20/F M</b>	20	VTL 20/F M	1 ~ 230-50Hz	DO 06 90	430	360	270	54.5	FB 20 / FC 20
<b>DO 20 MV 20</b>	20	MV 20	3 ~ 230/400-50Hz	DO 06 92	430	315	270	45.5	FB 20 / FC 20
<b>DO 20 MV 20 M</b>	20	MV 20 M	1 ~ 230-50Hz	DO 06 90	430	315	270	46.0	FB 20 / FC 20

N.B.: La pompa MV 20 è dotata, di serie, del filtro FC 20 sull'aspirazione.

Rapporti di trasformazione: inch =  $\frac{mm}{25.4}$ ; pounds =  $\frac{g}{453.6} = \frac{Kg}{0.4536}$

Adattatori per filettature GAS - NPT disponibili a pag. 1.117